

Quantum limits on detection sensitivity of a linear detector with feedback

Yang Gao*

Department of Physics, Xinyang Normal University, Xinyang, Henan 464000, China

We show that the detection sensitivity of a linear detector is lower bounded by some quantum limits. For the force detection, relevant for atomic force microscopes, the lower bound is given by the so-called ultimate quantum limit. For the displacement detection, relevant for detecting gravitational waves, a generalized lower bound is obtained.

PACS numbers: 03.65.Ta, 04.80.Nn, 42.50.Lc, 42.50.Wk

I. INTRODUCTION

It is known that an optomechanical system, i.e., a mechanical oscillator coupled to an optical cavity by radiation pressure, could be a sensitive detector for very weak forces or tiny displacements. Some examples are atomic force microscopes [1] and interferometers for detecting gravitational waves [2]. For a typical optomechanical detector, the detection sensitivity is lower bounded by the so-called standard quantum limit (SQL) due to quantum noises [3–5].

However, the SQL itself is not a fundamental quantum limit. Different schemes to overcome the SQL have been proposed, such as frequency dependent squeezing (FDS) of the input beam [6, 7], cavity detuning (CD) [8], variational measurement (VM) [9], quantum locking of the mirror [10], coherent quantum noise cancellation (CQNC) [11], and etc. It is shown in Ref. [12] that the fundamental quantum limit for the force sensitivity of a linear detector is given by the so-called ultimate quantum limit (UQL) in Refs. [7, 8]. This UQL is related to the dissipation mechanism of the oscillator, via the absolute value of the imaginary part of the inverse mechanical susceptibility. It also holds for the cases with coherent quantum control and/or with simple direct quantum feedback [13, 14]. Now we try to extend the result in Ref. [12] to the cases with more complicated quantum feedback loop, such as quantum locking of the mirror via a control cavity [10].

On the other hand, for the displacement sensitivity, we find that the usual UQL, given by the absolute value of the imaginary part of the mechanical susceptibility, can be overcome by some devised schemes. Moreover, a generalized quantum limit on the displacement sensitivity can be obtained following the similar arguments for quantum limit on the force sensitivity.

The paper is organized as follows. In Section II, we prove the UQL for the force sensitivity of a linear detector in the presence of direct quantum feedback by using the general linear-response theory. The results are then adjusted to establish a general quantum limit on the displacement sensitivity. Section III contains some




FIG. 1: Schematics of (a) a generic linear-response detector and (b) an optomechanical detector. The outputs Y, Z from the photodiodes are modulated by the local oscillator (LO) phases.

illustrating examples for the above results. At last, a short summary is given in Section IV.

II. DETECTION SENSITIVITY OF A LINEAR DETECTOR WITH FEEDBACK

We consider a generic linear-response detector (see Fig. 1(a)). It is described by some unspecified Hamiltonian H_d , and has both an input operator, represented by an operator F , and an output operator, represented by an operator Z . The detector is used to estimate a classical force $f(t)$ applied on a mechanical oscillator, which is represented by the Hamiltonian H_m . The input operator F is coupled with the mechanical oscillator via the interaction Hamiltonian, $H_{int} = -q(f + gF)$, where q is the displacement operator of the oscillator. The output operator Z (e.g., the output optical quadrature) is related to the readout quantity at the output of the detector (e.g., the output current of the photodiode), from which the

*Electronic address: gaoyangchang@outlook.com

information of the classical force can be inferred.

The total Hamiltonian is given by $H = H_m + H_d + H_{int}$. Treating H_{int} as the perturbation, an arbitrary operator O in the Heisenberg picture is obtained by

$$O(t) = \mathcal{U}^\dagger O_0(t) \mathcal{U}, \quad \mathcal{U}(t) = \mathcal{T} e^{-i \int_{-\infty}^t H_{int}^0(t') dt'}, \quad (1)$$

where $O_0(t)$ denotes the operator in the interaction picture, and the symbol $\mathcal{T}$ means the time-ordered product. For the linear operators q , F , and Z (with the c-number commutators), Eq. (1) gives the equation of motion in the frequency domain [10],

$$\begin{aligned} q &= q_0 + q_f + g\chi_{qq}F, \\ F &= F_0 + g\chi_{FF}q, \\ Z &= Z_0 + gq, \end{aligned} \quad (2)$$

where $q_f = \chi_{qq}f$, and Z is the rescaled output operator via $Z(\omega) = \chi_{ZF}(\omega)Z(\omega)$. The susceptibility $\chi_{O_1O_2}$ is defined by the c-number commutator, $\chi_{O_1O_2}(t) = i\theta(t)[O_1(t), O_2(0)]$.

Solving the first two equations and substituting into the third one of Eq. (2), we have the output operator in terms of the unperturbed operators,

$$Z = Z_0 + g \frac{q_0 + q_f + g\chi_{qq}F_0}{1 - g^2\chi_{qq}\chi_{FF}}. \quad (3)$$

It then gives an unbiased estimator q_{est} of q_f , $q_{\text{est}} = q_f + \hat{q}_f$, where the added noise $\hat{q}_f$ is

$$\hat{q}_f = q_0 + g\chi_{qq}F_0 + \frac{Z_0}{g}(1 - g^2\chi_{qq}\chi_{FF}). \quad (4)$$

Here the first term is the intrinsic mechanical noise, the second term is the backaction noise from the oscillator, and the third term is the shot noise at the output. Neglecting the intrinsic mechanical noise from now on, the force sensitivity can be characterized by the power spectrum $S_{\hat{q}_f\hat{q}_f}$ defined by the correlation

$$\frac{1}{2}\langle O_1(\omega)O_2^\dagger(\omega') + O_2^\dagger(\omega')O_1(\omega) \rangle = S_{O_1O_2}\delta(\omega - \omega'). \quad (5)$$

Using the uncertainty relation for F_0 and Z_0 , the optimization of $S_{\hat{q}_f\hat{q}_f}$ over the coupling strength g gives

$$S_{\hat{q}_f\hat{q}_f} \geq |\chi_{qq}^I|, \quad (6)$$

where χ_{qq}^I is the imaginary part of the susceptibility $\chi_{qq} = \chi_{qq}^R + i\chi_{qq}^I$. Equivalently, the force sensitivity in terms of f yields

$$S_f = \frac{S_{\hat{q}_f\hat{q}_f}}{|\chi_{qq}^I|} \geq |\bar{\chi}_{qq}^I|, \quad (7)$$

where $\bar{\chi}_{qq} = 1/\chi_{qq}$ is the inverse mechanical susceptibility. This is the UQL for the force sensitivity.

The above result has incorporated the effect of coherent quantum control [13], such as the CNQC scheme. As

for the direct quantum feedback control [14], a control signal $\mathcal{Y}(t)$ is fed back to the system, see Fig. 1(a). For a generic operator O , it introduces an additional term to the equation of motion,

$$\dot{O}_{fb}(t) = i \int_{-\infty}^t dt' \tilde{\lambda}(t-t') \mathcal{Y}(t') [\mathcal{P}(t), O(t)], \quad (8)$$

where $\tilde{\lambda}(t)$ is the feedback transfer function, $\mathcal{P}(t)$ is the control operator. If the linear control operator $\mathcal{P}$ is of the mechanical oscillator, $[\mathcal{P}, q] = \text{const.}$ and $[\mathcal{P}, F] = 0$. In the frequency domain, we have $q_{fb} = \lambda Y$, where λ is the rescaled transfer function.

It has been shown in Ref. [12] that if the measured signal is the same as the control signal fed back to the system ($Z = \mathcal{Y}$), the force sensitivity does not change. On the other hand, if the measured signal is different from the control signal ($Z \neq \mathcal{Y}$), such as the cases of quantum locking of the mirror, the equation of motion becomes

$$\begin{aligned} q &= q_0 + q_f + g\chi_{qq}F + \lambda Y, \\ F &= F_0 + g\chi_{FF}q, \\ Y &= Y_0 + gq, \\ Z &= Z_0 + gq. \end{aligned} \quad (9)$$

We find that

$$q = \frac{q_0 + q_f + \lambda Y_0 + g\chi_{qq}F_0}{1 - g\lambda - g^2\chi_{qq}\chi_{FF}}. \quad (10)$$

The estimator of q_f deduced from the measured signal Z thus is $q_{\text{est}} = q_f + \hat{q}_f$ with the added noise

$$\hat{q}_f = q_0 + g\chi_{qq}F_0 + \lambda Y_0 + \frac{Z_0}{g}(1 - g\lambda - g^2\chi_{qq}\chi_{FF}). \quad (11)$$

We find that for $Z = Y$, the above equation reduces to Eq. (4).

To find a lower bound to the power spectrum of $\hat{q}_f$, we first optimize $S_{\hat{q}_f\hat{q}_f}$ over the transfer function λ and the coupling strength g , respectively. This leads to

$$S_{\hat{q}_f\hat{q}_f} \geq \frac{2(A\chi_{qq}^R + B\chi_{qq}^I + |\chi_{qq}|\sqrt{C})}{S_{YY} + S_{ZZ}}, \quad (12)$$

where the notations are

$$\begin{aligned} A &= S_{ZF}^R S_{YY} + S_{YF}^R S_{ZZ} - \chi_{FF}^R S_{YY} S_{ZZ} \\ B &= S_{ZF}^I S_{YY} + S_{YF}^I S_{ZZ} + \chi_{FF}^I S_{YY} S_{ZZ} \\ C &= [S_{FF}(S_{YY} + S_{ZZ}) + |\chi_{FF}|^2 S_{YY} S_{ZZ} \\ &\quad - (S_{YF}^I - S_{ZF}^I)^2 - (S_{YF}^R - S_{ZF}^R)^2 \\ &\quad + 2S_{YY}(\chi_{FF}^I S_{ZF}^I - \chi_{FF}^R S_{ZF}^R) \\ &\quad + 2S_{ZZ}(\chi_{FF}^I S_{YF}^I - \chi_{FF}^R S_{YF}^R)] S_{YY} S_{ZZ}. \end{aligned} \quad (13)$$

Next, we note that $[Y_0(t), Y_0(t')] = [Z_0(t), Z_0(t')] = 0$ at all times, in order for $Y_0(t)$ and $Z_0(t)$ to represent experimental data strings. It immediately implies that $\chi_{YY} =$

$\chi_{ZZ} = 0$. Also, the causality principle imposes that the outputs $Y_0(t)$ and $Z_0(t)$ should not depend on the input $F_0(t')$ for $t < t'$, and therefore $\chi_{FY}(\omega) = \chi_{FZ}(\omega) = 0$. Furthermore, Y_0 , Z_0 , and F_0 should satisfy the uncertainty relation [3, 12] implied by the positivity of the matrix $M_{jk} = S_{jk} \pm i[\chi_{jk} - \chi_{kj}^*]/2$ with the indexes $j, k = Y_0, Z_0, F_0$,

$$M = \begin{bmatrix} S_{YY} & 0 & S_{YF} \pm i/2 \\ 0 & S_{ZZ} & S_{ZF} \pm i/2 \\ S_{YF}^* \mp i/2 & S_{ZF}^* \mp i/2 & S_{FF} \mp \chi_{FF}^I \end{bmatrix} \geq 0 \quad (14)$$

or equivalently,

$$S_{FF}S_{YY}S_{ZZ} \geq \frac{S_{YY} + S_{ZZ}}{4} \pm (S_{ZF}^I S_{YY} + S_{YF}^I S_{ZZ}) + |S_{ZF}|^2 S_{YY} + |S_{YF}|^2 S_{ZZ} \pm \chi_{FF}^I S_{YY} S_{ZZ}. \quad (15)$$

Here the relations $\chi_{YF} - \chi_{FY}^* = \chi_{ZF} - \chi_{FZ}^* = 1$ and $S_{jk} = S_{kj}^*$ have been used.

Substituting this inequality into Eq. (13), by some calculations we find

$$\begin{aligned} C &\geq A^2 + \left(B \pm \frac{S_{YY} + S_{ZZ}}{2} \right)^2 \\ &= A^2 + \left(|B| + \frac{S_{YY} + S_{ZZ}}{2} \right)^2. \end{aligned} \quad (16)$$

Then from Eq. (12), we finally obtain

$$S_{\hat{q}_f \hat{q}_f} \geq |\chi_{qq}^I|, \quad (17)$$

where the inequalities $a_1 x_1 + \sqrt{(a_1^2 + a_2^2)(x_1^2 + x_2^2)} \geq |a_2 x_2|$ and $|a| \geq a$ have been used. The force sensitivity S_f is then given by

$$S_f \geq |\bar{\chi}_{qq}^I|, \quad (18)$$

which is the main result of this paper. Similar result can be obtained if the control operator $\mathcal{P}$ is from the detector. The UQL is thus established in the presence of direct quantum feedback.

Now we show whether the displacement sensitivity S_q is lower bounded by $|\chi_{qq}^I|$, namely, the usual UQL for the displacement sensitivity. It is known that this UQL is valid in the weak coupling limit and/or for a detector with a large power gain [3, 5]. In general, the displacement sensitivity is given by the power spectrum of the estimator q_{est} of q deduced from the measured signal Z , $q_{\text{est}} = Z/g = q + \hat{q}$, where the added noise is

$$\hat{q} = \frac{\hat{q}_f}{1 - g\lambda - g^2\chi_{qq}\chi_{FF}}. \quad (19)$$

Then we get

$$\begin{aligned} S_q &= S_{\hat{q}\hat{q}} = \frac{S_{\hat{q}_f \hat{q}_f}}{|1 - g\lambda - g^2\chi_{qq}\chi_{FF}|^2} \\ &\geq \frac{|\chi_{qq}^I|}{|1 - g\lambda - g^2\chi_{qq}\chi_{FF}|^2}, \end{aligned} \quad (20)$$

which can therefore overcome the UQL by properly adjusting the detector parameters to make the above denominator larger than one, as illustrated in the subsequent examples. We also note that in the weak coupling limit, the denominator is approximately equal to one, and Eq. (20) reduces to the UQL.

III. CAVITY DETUNING AND QUANTUM LOCKING OF THE MIRROR

To exemplify the results in the last section, we take the optomechanical detector as an example. The optomechanical detector consists of a high quality Fabry-Perot cavity, with a fixed transmissive mirror in front of the cavity, and a moveable, perfectly reflecting mirror m at the back (see Fig. 1(b)). The cavity field described by the annihilation operator $b = (b_1 + ib_2)/\sqrt{2}$ with resonant frequency ω_b is fed with a driving laser β_{in} . The aim is to estimate a classical force $f(t)$ acting on the moveable mirror described by the annihilation operator $a = (q + ip)/\sqrt{2}$ with frequency Ω . In the rotating frame at the frequency ω_0 of the driving laser, the system is described by the Hamiltonian,

$$\begin{aligned} H &= H_m + H_d + H_{int} \\ &= \Omega a^\dagger a + [\Delta b^\dagger b + i\sqrt{\gamma}(\beta_{in} b^\dagger - \beta_{in}^* b)] \\ &\quad - q[f + g_{om}(b^\dagger b - \langle b^\dagger b \rangle)], \end{aligned} \quad (21)$$

where $\Delta = \omega_b - \omega_0$ is the cavity detuning, and g_{om} is the optomechanical coupling strength. Taking into account the thermal noises, the equations of motion are given by the quantum Langevin equations [15],

$$\begin{aligned} \dot{a} &= -i\Omega a - \frac{\Gamma}{2}a + [f + g_{om}(b^\dagger b - \langle b^\dagger b \rangle)]/\sqrt{2} + \sqrt{\Gamma}a_{in}, \\ \dot{b} &= -i\Delta b - \frac{\gamma}{2}b + ig_{om}qb + \sqrt{\gamma}(\beta_{in} + b_{in}), \end{aligned} \quad (22)$$

where $\Gamma(\gamma)$ and $a_{in}(b_{in})$ are the decay rate and thermal noise operator for the oscillator (cavity), respectively. The noise correlations are given by $\langle a_{in}(t)a_{in}^\dagger(t') \rangle = (n_{th} + 1)\delta(t - t')$ and $\langle b_{in}(t)b_{in}^\dagger(t') \rangle = \delta(t - t')$, where n_{th} is the thermal occupancy of the mechanical reservoir.

Under the condition of strong laser driving, we can linearized Eq. (22) around the steady state, $\langle a \rangle = 0$ and $\langle b \rangle = \beta = \sqrt{\gamma}\beta_{in}/(\gamma/2 + i\Delta)$, by splitting $a \rightarrow \langle a \rangle + a$ and $b \rightarrow \langle b \rangle + b$. Neglecting the nonlinear terms, we have

$$\dot{\mathbf{x}} = \mathbf{A}\mathbf{x} + \mathbf{w}, \quad (23)$$

where the variables $\mathbf{x} = (q, p, b_1, b_2)^\top$, the input $\mathbf{w} = (\sqrt{\Gamma}q_{in}, f + \sqrt{\Gamma}p_{in}, \sqrt{\gamma}b_{in}^1, \sqrt{\gamma}b_{in}^2)^\top$, and the matrix

$$\mathbf{A} = \begin{pmatrix} -\frac{\Gamma}{2} & \Omega & 0 & 0 \\ -\Omega & -\frac{\Gamma}{2} & g & 0 \\ 0 & 0 & -\frac{\gamma}{2} & \Delta \\ g & 0 & -\Delta & -\frac{\gamma}{2} \end{pmatrix} \quad (24)$$




FIG. 2: Plots of the force sensitivity (a) and the displacement sensitivity (b) with respect to the detection frequency for the optomechanical detector. Grey: SQL; green: UQL; blue: detuned cavity for $\gamma = 2$, $g = 5$, $\Delta = -5$, and $\tan \phi = -1$; red: resonant cavity with feedback for $g = g/2 = 1$, $\phi = 0$, (a) $\gamma = 5$, $\tan \theta = 2$, and (b) $\gamma = 2$, $\theta = 0$. Here the detection sensitivities are optimized over the feedback transfer function $\lambda(\omega)$. The common parameters are $\Omega = \Gamma = 0.1$.

in terms of the effective optomechanical coupling strength $g = \sqrt{2}g_{om}\beta$. The stability of this linearized system is guaranteed by the requirement that the real part of all the eigenvalues of $\mathbf{A}$ must be nonpositive. The classical force is then estimated from the output current I_{out} of a photodiode that is linearly proportional to a certain optical quadrature of the output field, $I_{out} \propto \mathcal{Z} = b_1^{out} \sin \phi + b_2^{out} \cos \phi$, where the output field is obtained by the input-output relation $b_{out} = \sqrt{\gamma}b - b_{in}$, and ϕ is the adjustable readout quadrature angle via the local oscillator phase. For the stationary state, Eq. (23) can be simply solved in the frequency domain. The corresponding numerical results for the detection sensitivities are shown in Fig. 2. It can be seen that for a detuned cavity, the force sensitivity is lower bounded by the relevant UQL, $S_f \geq |\chi_{qq}^I| = \omega\Gamma/\Omega$ with $\chi_{qq} = \Omega [(\Gamma/2 - i\omega)^2 + \Omega^2]^{-1}$, and the displacement sensitivity can overcome the corresponding UQL, namely, $S_q < |\chi_{qq}^I|$.

For the displacement sensitivity, it is also found that the usual UQL is still valid for a resonant cavity. Because the susceptibility $\chi_{FF} \propto \Delta$ with the operator $F = b_1$ for the optomechanical detector, and the denominator in Eq. (20) becomes unity for $\Delta = 0$. However, there is another possibility to overcome the usual UQL for a resonant cavity with the help of quantum feedback ($\lambda \neq 0$), such as quantum locking of the mirror. In this scheme, the addition of a feedback loop is used to suppress radiation pressure effects by freezing the motion of mirror. The mirror motion is monitored by a feedback force $\propto \mathcal{Y} = c_1^{out} \sin \theta + c_2^{out} \cos \theta$ from another resonant cavity made of the movable mirror m and a fixed transmissive,

reference mirror. The control system is governed by the Hamiltonian,

$$H_c = i\sqrt{\gamma}(\beta_{in}^c c^\dagger - \beta_{in}^{c*} c) + g_{om}q(c^\dagger c - \langle c^\dagger c \rangle), \quad (25)$$

where the control cavity field c with frequency ω_c is in resonance with the driving laser β_{in}^c , and takes the same decay rate γ as the main cavity.

The linearized equations of motion take the same form of Eq. (23), where

$$\begin{aligned} \mathbf{x} &= (q, p, b_1, b_2, c_1, c_2)^\top, \\ \mathbf{A} &= \begin{pmatrix} -\frac{\Gamma}{2} & \Omega & 0 & 0 & 0 & 0 \\ -\Omega & -\frac{\Gamma}{2} & g & 0 & -g_1 & g_2 \\ 0 & 0 & -\frac{\gamma}{2} & 0 & 0 & 0 \\ g & 0 & 0 & -\frac{\gamma}{2} & 0 & 0 \\ 0 & 0 & 0 & 0 & -\frac{\gamma}{2} & 0 \\ -g & 0 & 0 & 0 & 0 & -\frac{\gamma}{2} \end{pmatrix}, \\ \mathbf{w} &= (\sqrt{\Gamma}q_{in}, f_{\text{eff}}, \sqrt{\gamma}b_1^{in}, \sqrt{\gamma}b_2^{in}, \sqrt{\gamma}c_1^{in}, \sqrt{\gamma}c_2^{in})^\top \end{aligned} \quad (26)$$

in terms of the effective force $f_{\text{eff}} = f + \sqrt{\Gamma}p_{in} - \lambda(c_1^{in} \sin \theta + c_2^{in} \cos \theta)$, the effective coupling strengthes $g = 2g_{om}\beta_{in}\sqrt{2/\gamma}$, $g = 2g_{om}\beta_{in}^c\sqrt{2/\gamma}$, $g_1 = g - \lambda\sqrt{\gamma}\sin \theta$, and $g_2 = \lambda\sqrt{\gamma}\cos \theta$. The detection sensitivities obtained from the output current $I_{out} \propto \mathcal{Z} = b_1^{out} \sin \phi + b_2^{out} \cos \phi$ are also plotted in Fig. 2. It shows that for a resonant cavity with a feedback loop, the force sensitivity is still lower bounded by the UQL, and the displacement sensitivity can overcome the usual UQL by properly choosing detector parameters.

IV. CONCLUSION

We have proven the UQL for the force sensitivity of a generic linear-response detector in the presence of direct quantum feedback by using the general linear-response theory. We have shown that the usual UQL for the displacement sensitivity can be overcome by some devised schemes. By adopting the arguments for the force sensitivity, a generalized quantum limit is obtained for the displacement sensitivity. To illustrate the utilities of these quantum limits, we have taken a detuned cavity and a resonant cavity with a feedback loop as two specific examples. We believe that our results show the ways to improve the performance of high-sensitivity detection schemes.

YG acknowledges the support from NSFC Grant No. 11304265.

-
- [1] F. J. Giessibl, Rev. Mod. Phys. **75**, 949 (2003)
 - [2] The LIGO Scientific Collaboration and the Virgo Collaboration, Phys. Rev. Lett. **116**, 061102 (2016).
 - [3] V.B. Braginsky and F.Y. Khalili, *Quantum Measurement*

- (Cambridge University Press, Cambridge, 1992).
- [4] C.M. Caves, *et al.*, Rev. Mod. Phys. **52**, 341 (1980); C.M. Caves, Phys. Rev. D **23**, 1693 (1981).
- [5] A.A. Clerk, *et al.*, Rev. Mod. Phys. **82**, 1155 (2010).

- [6] R. Bondurant and J. Shapiro, Phys. Rev. D **30**, 2548 (1984).
- [7] M.T. Jaekel and S. Reynaud, Europhys. Lett. **13**, 301 (1990).
- [8] O. Arcizet, T. Briant, A. Heidmann, and M. Pinard, Phys. Rev. A **73**, 033819 (2006).
- [9] H. Kimble, *et al.*, Phys. Rev. D **65**, 022002 (2001).
- [10] J. M. Courty, A. Heidmann, and M. Pinard Phys. Rev. Lett. **90**, 083601 (2003).
- [11] M. Tsang and C.M. Caves, Phys. Rev. Lett. **105**, 123601 (2010); M.H. Wimmer, D. Steinmeyer, K. Hammerer, and M. Heurs, Phys. Rev. A **89**, 053836 (2014).
- [12] Y. Gao, H. Ho, and H. Zhang arXiv: 1602.08586.
- [13] N. Yamamoto, Phys. Rev. X **4**, 041029 (2014).
- [14] H.M. Wiseman and G.J. Milburn, *Quantum Measurement and Control* (Cambridge University Press, Cambridge, 2014).
- [15] D.F. Walls and G.J. Milburn, *Quantum Optics* (Springer, Berlin, 1994).